

SUNWAVE

SRC-3060 *Simplify your life!*



- *8 In One - Integrates up to 8 home devices into one remote control.*
- *Smart learning guide – Guides you how to program step by step.*
- *Macro Feature- Allows you to store up to 60 commands within one key!*
- *A large touch screen – Shows a clean surface and hi-tech texture.*
- *Cool Orange Backlight increases visibility in the dark.*
- *Full touch screen matches your unique taste.*
- *PC software support.*



Features

- ◆ Enable to control up to 8 devices.
- ◆ Orange LED backlight matches the housing color perfectly and stands out in the dark.
- ◆ Macro function is capable to store up to 60 series commands per macro key and also allows time delay between commands.
- ◆ Redesigned learning function provides solution for both existing tricky and upcoming new codes at the same time.
- ◆ "Pick Up Sensor" not only turns on and off the remote automatically, but also saves power when not using the remote.
- ◆ "Auto Set-up Saving" protects user's set-up from losing even taking batteries off.
- ◆ "Low Power Indicator" reminds user of power low condition by showing a warning sign on the screen.
- ◆ Optional on-line support allows user to upgrade the latest version of software by internet.

Specifications

- Dimensions (H x W x D): 186 x 80 x 24 mm
- Weight(without batteries): 7.4 oz(210 g)
- Memory: 512KB Flash memory
- Keys: 56 Keys/ 2 Pages/ 8 Device
- Learning Frequency: 20KHz - 455KHz & Pulse up to 256 bits long
- Backlight: Orange LED
- Interface: UART/ 115,200bps (Optional SLC-2080 USB Cable)
- IR Distance: 8 - 10 meters
- Batteries: 1.5V 3 X AAA Alkaline Batteries (SUM-4)
- Power Consumption
 - Operation current: 190 mA (max)
 - LCD on current: 180 μ A
 - LCD off current: 30 μ A



This device complies with Part 15 of the FCC rules.

SUNWAVE

Simple Control, Easy Life

Mail: info@sunwave.com.tw <http://www.sun-wave.com>

Tel: +886-2-8751-8555 Fax: +886-2-8751-8287

Address: 6F-5, No. 103, RuiHu St., Neihu District, Taipei, Taiwan 114